930N-7208-PS02 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF4 DF3 DF2 DF1 PF1 PF2 PF3 PF4
DC PC
DA PA
DR4 DR3 DR2 DR1 PR1 PR2 PR3 PR4

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION		
		REAR / ALLEY STROBES	FRONT / CORNER STROBES	ALLEY HALOGEN FLASHERS
1	ORG & BLU (CLEARING THE RIGHT OF WAY)	DR4 & PR4 SIMULTANEOUS AND ALTERNATE WITH DR1 & PR1 SIMULTANEOUS (6 PULSES PER BURST) DR2 ALTERNATES WITH PR2 (6 PULSES PER BURST) DR3 ALTERNATES WITH PR3 (3 PULSES PER BURST) DA ALTERNATES WITH PA (3 PULSES PER BURST)	DF4 & PF4 SIMULTANEOUS AND ALTERNATE WITH DF1 & PF1 SIMULTANEOUS (6 PULSES PER BURST) DF2 ALTERNATES WITH PF2 (6 PULSES PER BURST) DF3 ALTERNATES WITH PF3 (3 PULSES PER BURST) DC ALTERNATES WITH PC (3 PULSES PER BURST)	DA ALTERNATES WITH PA
2	BLU (BLOCKING THE RIGHT OF WAY)	SAME AS MODE 1	DF4 & PF4 SIMULTANEOUS AND ALTERNATE WITH DF3 & PF3 SIMULTANEOUS (6 PULSES PER BURST) DF2 ALTERNATES WITH PF2 (6 PULSES PER BURST) DC ALTERNATES WITH PC (3 PULSES PER BURST)	DA ALTERNATES WITH PA

OPTIONAL 930-PRE PREEMPTION EMITTER

Forward facing strobes will emit a High or Low priority preemption signal

C.R.O.W.	**PREEMPTION SIGNAL EMITTED**
C.R.O.W. + WHT/BLK	Standard NEOBE® Flash Rate

NOTE:

1. **The 930N-7208-PS02 is factory wired for High Intensity to meet NFPA specifications.**
2. **Apply +12vdc to appropriate control wire to activate desired function.**