

465NH-4805 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF2
DF1L/DF1R
FCL/FCR
PF1L/PF1R
PF2

DC

PC

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION FRONT / CORNER STROBES & HALOGENS
0	NONE	NONE
1	ORG	DF1L, FCR, PF1L SIMULTANEOUS ALTERNATES WITH DF1R, FCL, PF1R SIMULTANEOUS DF2 ALTERNATES WITH PF2 *DC ALTERNATES WITH PC* (*IF ORDERED WITH OPTIONAL STROBE OR HALOGEN)
RIGHT ARROW	BLU	DF1L, DF1L & DF1R, DF1L & DF1R & FCL, DF1L & DF1R & FCL & FCR, DF1L & DF1R & FCL & FCR & PF1L, DF1L & DF1R & FCL & FCR & PF1L & PF1R, REPEAT DF2 ALTERNATES WITH PF2 *DC ALTERNATES WITH PC* (*IF ORDERED WITH OPTIONAL STROBE)
LEFT ARROW	WHT/BLK	PF1R, PF1R & PF1L, PF1R & PF1L & FCR, PF1R & PF1L & FCR & FCL, PF1R & PF1L & FCR & FCL & DF1R, PF1R & PF1L & FCR & FCL & DF1R & DF1L, REPEAT DF2 ALTERNATES WITH PF2 *DC ALTERNATES WITH PC* (*IF ORDERED WITH OPTIONAL STROBE)
CENTER OUT	BLU & WHT/BLK	FCL & FCR, DF1R & FCL & FCR & PF1L, DF1L & DF1R & FCL & FCR & PF1L & PF1R, DF1L & DF1R & FCL & FCR & PF1L & PF1R, REPEAT DF2 ALTERNATES WITH PF2 *DC ALTERNATES WITH PC* (*IF ORDERED WITH OPTIONAL STROBE)
SWEEP	ORG & WHT/BLK	DF1L, DF1R & FCL, FCR & PF1L, PF1R, FCR & PF1L, DF1R & FCL, REPEAT DF2 ALTERNATES WITH PF2 *DC ALTERNATES WITH PC* (*IF ORDERED WITH OPTIONAL HALOGEN)

NOTE: GREEN control wire activates high intensity to strobes.
 Apply +12vdc to appropriate control wire to activate desired function.
 Cut loop (22 AWG BLACK) on 930H-8A (halogen controller) to select low current arrow patterns.