465N-9611 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF5 DF4 DF3 DF2 DF1 FCL/FCR PF1 PF2 PF3 PF4 PF5
DC PC

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION STROBES
1	ORG	DF1 & PF1 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMUTANEOUS (6 PULSES PER BURST) DF3 & PF4 SIMULTANEOUS AND ALTERNATE WITH DF4 & PF3 SIMUTANEOUS (6 PULSES PER BURST) DF5 ALTERNATES WITH PF5 (3 PULSES PER BURST)
2	ORG & BLU	DF1 & PF1 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMUTANEOUS (6 PULSES PER BURST) DF3 & DC SIMULTANEOUS AND ALTERNATE WITH PF3 & PC SIMUTANEOUS (6 PULSES PER BURST) DF4 ALTERNATES WITH PF4 (3 PULSES PER BURST) DF5 ALTERNATES WITH PF5 (3 PULSES PER BURST)
3	ORG & BLU & WHT/BLK *PREEMPTION	FCL ALTERNATES WITH FCR (3 PULSES PER BURST) DF1 & PF1 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMUTANEOUS (6 PULSES PER BURST) DF3 & DC SIMULTANEOUS AND ALTERNATE WITH PF3 & PC SIMUTANEOUS (6 PULSES PER BURST) DF4 ALTERNATES WITH PF4 (3 PULSES PER BURST) DF5 ALTERNATES WITH PF5 (3 PULSES PER BURST)

*PREEMPTION SIGNAL IN MODE 3 – IF PRE OPTION IS ORDERED

*CONTROL WIRES FOR OPTIONAL PREEMPTION EMITTER

CONTROL WIRE ACTIVATED

BRN/WHT PARKING BRAKE OVERRIDE

Activation will change the flash rate from PREEMPTION to standard NEOBE™.

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP	
BRN	DF1 & PF1	SPLIT TAKEDOWN

Or **OPTIONAL Dual Mode Halogen Operation**

BRN	DF1 & PF1	SPLIT FRONT FLASHER
RED/WHT	DF1 & PF1	STEADYBURN ACTIVATION

NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.