

930N-2402-LS01 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF1 PF1
 DC PC
 DA PA
 DR1 PR1

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION
		FRONT / CORNER and REAR / ALLEY STROBES
0	NONE	NONE
1	BLU (BLOCKING THE RIGHT OF WAY)	PF1 & PR1 SIMULTANEOUS AND ALTERNATE WITH DF1 & DR1 SIMULTANEOUS (6 PULSES PER BURST) DA ALTERNATES WITH PA (3 PULSES PER BURST)
2	ORG & BLU (CLEARING THE RIGHT OF WAY)	PF1 & PR1 SIMULTANEOUS AND ALTERNATES WITH DC & PC SIMULTANEOUS (6 PULSES PER BURST) DF1 ALTERNATES WITH DR1 (3 PULSES PER BURST) DA ALTERNATES WITH PA (3 PULSES PER BURST)

NOTE:

1. The 930N-2402-LS01 Light Bar is factory wired for High Intensity operation to meet NFPA specifications.
2. Apply +12vdc to appropriate control wire to activate desired function.