930N-6407-0027 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF3 DF2 DF1 FC PF1 PF2 PF3
DC PC
DA PA
DR3 DR2 DR1 RC PR1 PR2 PR3

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES	FRONT / CORNER STROBES
0	NONE	NONE	NONE
ALL STROBES	ORG	DR3, PR3 & PA SIMULTANEOUS AND ALTERNATE WITH DR2, PR2 & DA SIMULTANEOUS (6 PULSES PER BURST) DR1, RC, PR1, RC, REPEAT (3 PULSES PER BURST)	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS (6 PULSES PER BURST) DF1, FC, PF1, FC, REPEAT (3 PULSES PER BURST) DC ALTERNATES WITH PC (3 PULSES PER BURST)
FRONT ONLY	ORG & BLU	DA ALTERNATES WITH PA	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS (6 PULSES PER BURST) DF1, FC, PF1, FC, REPEAT (3 PULSES PER BURST) DC ALTERNATES WITH PC (3 PULSES PER BURST)
REAR ONLY	ORG & WHT/BLK	DR3, PR3 & PA SIMULTANEOUS AND ALTERNATE WITH DR2, PR2 & DA SIMULTANEOUS (6 PULSES PER BURST) DR1, RC, PR1, RC, REPEAT (3 PULSES PER BURST)	NONE
RIGHT ARROW	BLU	DR3, DR3 & DR2, DR2 & DR1, DR1 & RC, RC & PR1, PR1 & PR2, PR2 & PR3, PR3, REPEAT DA ALTERNATES WITH PA	DC ALTERNATES WITH PC
LEFT ARROW	WHT/BLK	PR3, PR3 & PR2, PR2 & PR1, PR1 & RC, RC & DR1, DR1 & DR2, DR2 & DR3, DR3, REPEAT DA ALTERNATES WITH PA	DC ALTERNATES WITH PC
CENTER OUT	BLU & WHT/BLK	RC, DR1 & RC & PR1, DR2 & DR1 & PR1 & PR2, DR3 & DR2 & PR2 & PR3, DR3 & PR3, REPEAT DA ALTERNATES WITH PA	DC ALTERNATES WITH PC

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP	
GRAY	DA	(DRIVER ALLEY)
YELLOW	PA	(PASSENGER ALLEY)
RED/WHT	DR1 & PR1	(SPLIT REAR WORK)
BRN	DF1 & PF1	(SPLIT TAKEDOWN)

NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.