

930NH-5606-0060 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF3 DF2 DF1 PF1 PF2 PF3
DC PC
DA PA
DR3 DR2 DR1 PR1 PR2 PR3

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES & HALOGENS	FRONT / CORNER STROBES & HALOGENS
1	ORG	DR3 & DR2 SIMULTANEOUS AND ALTERNATE WITH PR3 & PR2 SIMULTANEOUS	NONE
2	ORG & BLU	DR3 & DR2 SIMULTANEOUS AND ALTERNATE WITH PR3 & PR2 SIMULTANEOUS DA ALTERNATES WITH PA	DF3 & DF2 SIMULTANEOUS AND ALTERNATE WITH PF3 & PF2 SIMULTANEOUS
3	ORG & BLU & WHT/BLK	SAME AS MODE 2	DF3 & DF2 SIMULTANEOUS AND ALTERNATE WITH PF3 & PF2 SIMULTANEOUS DC ALTERNATES WITH PC (3 PULSES PER BURST)
STROBES ONLY	BLU	DR3 ALTERNATES WITH PR3	DF3 ALTERNATES WITH PF3 (6 PULSES PER BURST) DC ALTERNATES WITH PC (3 PULSES PER BURST)
HALOGENS ONLY (MODE 1)	WHT/BLK	DR2 ALTERNATES WITH PR2	NONE
HALOGENS ONLY (MODE 2)	ORG & WHT/BLK	DR2 ALTERNATES WITH PR2 DA ALTERNATES WITH PA	DF2 ALTERNATES WITH PF2

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP	
BROWN	DF1	TAKEDOWN
BROWN/WHITE	PR1	REAR WORK
GRAY	DR1	REAR WORK
YELLOW	DA & PA	ALLEY LAMPS

EXCLUSIVE OPTIONS

CONTROL WIRE ACTIVATED	LAMP	
RED/WHITE	PF1	TAKEDOWN
	OR PF1	PREEMPTION EMITTER
	OR DF1 & PF1	OPTIONAL STROBES

NOTE: Halogen lamps DF2, PF2, DR2 & PR2 each have 2 halogen bulbs per lamp. As indicated above, the Standard flash pattern specifies both bulbs in a lamp housing flash at the same time and alternate with another lamp housing. The 930NH-5606 Lightbar may also be ordered from the factory with the 930-HSPLIT-18 Option, in which case one halogen bulb in each lamp housing will alternate with 2nd halogen bulb in the same lamp housing.

NOTE: GREEN control wire activates high intensity to strobes.

Apply +12vdc to appropriate control wire to activate desired function.