465NH-8810-0102 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF5 DF4 DF3 DF2 DF1 PF1 PF2 PF3 PF4 PF5
DC PC

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION FRONT / CORNER STROBES & HALOGENS
HALOGEN WARNING MODE	ORG	DF1, DF2, PF3 & PF4 SIMULTANEOUS AND ALTERNATES WITH DF4, DF3, PF1 & PF2 SIMULTANEOUS
HALOGEN RIGHT ARROW	BLU	PF4, **PF4 & PF3**, PF4 & **PF3 & PF2**, PF4 & PF3 & **PF2 & PF1**, PF4 & PF3 & PF2 & **PF1 & DF1**, PF4 & PF3 & PF2 & PF1 & **DF1 & DF2**, PF4 & PF3 & PF2 & PF1 & DF1 & **DF2 & DF3**, PF4 & PF3 & PF2 & PF1 & DF1 & DF2 & **DF3 & DF4**, **REPEAT**
HALOGEN LEFT ARROW	WHT/BLK	DF4, **DF4 & DF3**, DF4 & **DF3 & DF2**, DF4 & DF3 & **DF2 & DF1**, DF4 & DF3 & DF2 & **DF1 & PF1**, DF4 & DF3 & DF2 & DF1 & **PF1 & PF2**, DF4 & DF3 & DF2 & DF1 & PF1 & **PF2 & PF3**, DF4 & DF3 & DF2 & DF1 & PF1 & PF2 & **PF3 & PF4**, **REPEAT**
HALOGEN CENTER OUT	BLU & WHT/BLK	**DF1 & PF1**, DF1 & PF1 & **DF2 & PF2**, DF1 & PF1 & DF2 & PF2 & **DF3 & PF3**, DF1 & PF1 & DF2 & PF2 & DF3 & PF3 & **DF4 & PF4**, **REPEAT**
HALOGEN SWEEP	ORG & WHT/BLK	PF4 & PF3, PF1 & PF2, DF1 & DF2, DF4 & DF3, THEN REVERSE ORDER, AND REPEAT.
STROBES	BRN/WHT	DF5 & PC SIMULTANEOUS AND ALTERNATES WITH PF5 & DC SIMULTANEOUS

NOTE: CUT BLACK CONTROL LOOP ON THE 930H-8A HALOGEN CONTROLLER FOR **LOW CURRENT ARROW** PATTERNS INDICATED IN BOLD & UNDERLINED ABOVE.

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMPS
BROWN	DF4L & PF4R SPLIT TAKEDOWN

NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.