

930NH-4805-0103 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

	DF2	DF1	FC	PF1	PF2
DC					PC
DA					PA
	DR2	DR1	RC	PR1	PR2

CONTROL WIRES ACTIVATED	LAMP OPERATION	
	HALOGENS	STROBES
ORG HALOGEN ONLY	DF1, PF1, DA-A & PA-A SIMULTANEOUS AND ALTERNATE DF2, PF2, DAF & PAF	NONE
BRN/WHT	NONE	DR2 & PR2 SIMULTANEOUS AND ALTERNATE WITH RCR & RCL SIMULTANEOUS
BRN	NONE	DR1 ALTERNATES WITH PR1
RED/WHT FRONT STROBES	NONE	FCL & FCR SIMULTANEOUS AND ALTERNATE WITH DC & PC SIMULTANEOUS

CONTROL WIRES FOR STEADYBURN SPLIT ALLEY HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP	
GRN	DA-A	DRIVER ALLEY
WHT/BLK	PA-A	PASSENGER ALLEY

**NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.**