930NH-4805-0024 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF2 DF1 FC PF1 PF2
DC PC
DA PA
DR2 DR1L/DR1R RCL/RCR PR1L/PR1R PR2

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES & HALOGENS	FRONT / CORNER STROBES & HALOGENS
0	NONE	NONE	NONE
1	ORG	DR2, DR1L, DR1R, RCL & PA SIMULTANEOUS AND ALTERNATE WITH PR2, PR1L, PR1R, RCR & DA SIMULTANEOUS	DC ALTERNATES WITH PC
2	ORG & BLU	DR2, DR1L, DR1R & RCL SIMULTANEOUS AND ALTERNATE WITH PR2, PR1L, PR1R & RCR SIMULTANEOUS DA ALTERNATES WITH PA	DF2 ALTERNATES WITH PF2 DC ALTERNATES WITH PC
3	ORG & BLU & WHT/BLK	SAME AS MODE 2	DF2 & DF1 SIMULTANEOUS AND ALTERNATE WITH PF2 & PF1 SIMULTANEOUS DC ALTERNATES WITH PC
RIGHT ARROW	BLU	DR1L, DR1L & DR1R, DR1L & DR1R & RCL, DR1L & DR1R & RCL & RCR, DR1L & DR1R & RCL & RCR & PR1L, DR1L & DR1R & RCL & RCR & PR1L & PR1R, REPEAT	NONE
LEFT ARROW	WHT/BLK	PR1R, PR1R & PR1L, PR1R & PR1L & RCR, PR1R & PR1L & RCR & RCL, PR1R & PR1L & RCR & RCL & DR1R, PR1R & PR1L & RCR & RCL & DR1R & DR1L, REPEAT	NONE
CENTER OUT	BLU & WHT/BLK	RCL & RCR, DR1R & RCL & RCR & PR1L, DR1L & DR1R & RCL & RCR & PR1L & PR1R, REPEAT	NONE
HALOGENS ONLY	ORG & WHT/BLK	DR1L, DR1R & RCL SIMULTANEOUS AND ALTERNATE WITH PR1L, PR1R & RCR SIMULTANEOUS	DF1 ALTERNATES WITH PF1

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP	
BROWN	FC	(TAKEDOWN)
GRAY	DA	(DRIVER ALLEY)
YELLOW	PA	(PASSENGER ALLEY)
BROWN/WHITE	DF1	(CA STEADY RED)

NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.
Cut loop (22 AWG BLACK) on 930N-8-0024 (NEOBE power supply) to enable FRONT strobes during traffic direction modes.
Cut loop (22 AWG BLACK) on 930H-8 (halogen controller) to select low current arrow patterns.