

## **930NH-2402 FLASH PATTERN**

### **LIGHTBAR LAMP CONFIGURATION**

DF1L / DF1R    PF1L / PF1R  
DC    PC  
DA    PA  
DR1L / DR1R    PR1L / PR1R

CONTROL WIRES ACTIVATED	LAMP OPERATION	
	REAR / ALLEY STROBES & HALOGENS	FRONT / CORNER STROBES & HALOGENS
ORG  STROBES ONLY	DR1L ALTERNATES WITH PR1R ( 6 PULSES PER BURST ) DA ALTERNATES WITH PA ( 3 PULSES PER BURST )	DF1L ALTERNATES WITH PF1R ( 6 PULSES PER BURST ) DC ALTERNATES WITH PC ( 3 PULSES PER BURST )
BRN  HALOGEN ONLY	DR1R ALTERNATES WITH PR1L	DF1R ALTERNATES WITH PF1L

### **CONTROL WIRES FOR OPTIONAL HALOGENS**

CONTROL WIRE ACTIVATED	HALOGEN LAMP
GRAY	DA    DRIVER ALLEY
YELLOW	PA    PASSENGER ALLEY

**NOTE: GREEN control wire activates high intensity to strobes.  
Apply +12vdc to appropriate control wire to activate desired function.**