

930N-4805-0071 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF2	DF1L/DF1R	FCL/FCR	PF1L/PF1R	PF2
DC				PC
DA				PA
DR2	DR1L/DR1R	RCL/RCR	PR1L/PR1R	PR2

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES	FRONT / CORNER STROBES
1	ORG (REAR ONLY)	DR2 ALTERNATES WITH PR2	NONE
2	ORG & BLU	DR2 & DA SIMULTANEOUS AND ALTERNATE WITH PR2 & PA SIMULTANEOUS	DF2 & PF2 SIMULTANEOUS AND ALTERNATE WITH FCL & FCR SIMULTANEOUS
3	ORG & BLU & WHT/BLK	DR2 & DA SIMULTANEOUS AND ALTERNATE WITH PR2 & PA SIMULTANEOUS	DF2 & PF2 SIMULTANEOUS AND ALTERNATE WITH FCL & FCR SIMULTANEOUS DC ALTERNATES WITH PC

CONTROL WIRES FOR STANDARD & OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP
BROWN	DF1R & PF1L FRONT FLASHER
BROWN/WHITE	DF1L & PF1R TAKEDOWN
GRAY	DA DRIVER ALLEY
YELLOW	PA PASSENGER ALLEY

CONTROL WIRE FOR OPTIONAL DUAL MODE HALOGEN

CONTROL WIRE ACTIVATED	HALOGEN LAMP
RED/WHT	DF1R & PF1L FRONT FLASHER – STEADYBURN ACTIVATION

CONTROL WIRE FOR OPTIONAL PRE2-1C PREEMPTION EMITTER

CONTROL WIRE ACTIVATED	STROBE LAMP
RED/WHT	FC

**NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.**

CONTROL WIRES FOR CUSTOMER CONTROLLED HALOGEN ARROW

TOMAR M1072 CABLE	CUSTOMER CONTROLLER	HALOGEN
NO CONNECTION	WHITE	
YELLOW	BROWN	DR1L
YELLOW/WHITE	GREEN	DR1R
RED	ORANGE	RCL
RED/WHITE	VIOLET	RCR
BLACK	GRAY	PR1L
BLACK/WHITE	YELLOW	PR1R
NO CONNECTION	BLUE	

Apply -12vdc to appropriate control wire to activate desired function.