# 930N-5606-0043 FLASH PATTERN

## LIGHTBAR LAMP CONFIGURATION

DF3 DF2 DF1 PF1 PF2 PF3
DC PC
DA PA
DR3 DR2 DR1 PR1 PR2 PR3

| MODE | CONTROL WIRES ACTIVATED | LAMP OPERATION | |
|---|---|---|---|
| | | REAR / ALLEY STROBES | FRONT / CORNER STROBES |
| 0 | NONE | NONE | NONE |
| 1 | ORG (REAR ONLY) | DR3, DR2, DR1, PR1, PR2, PR3, PR2, PR1, DR1, DR2, REPEAT (SWEEP) DA ALTERNATES WITH PA | NONE |
| 2 | ORG & BLU (FRONT ONLY) | DA ALTERNATES WITH PA | DF3, DF2, PF2, PF3, PF2, DF2, REPEAT (SWEEP) DC ALTERNATES WITH PC |
| 3 | ORG & BLU & WHT/BLK (360 +) | SAME AS MODE 1 (SWEEP) | SAME AS MODE 2 (SWEEP) |
| RIGHT ARROW | BLU | DR3, DR3 & DR2, DR2 & DR1, DR1 & PR1, PR1 & PR2, PR2 & PR3, PR3, DA & PA, REPEAT | SAME AS MODE 2 (SWEEP) |
| LEFT ARROW | WHT/BLK | PR3, PR3 & PR2, PR2 & PR1, PR1 & DR1, DR1 & DR2, DR2 & DR3, DR3, DA & PA, REPEAT | SAME AS MODE 2 (SWEEP) |
| CENTER OUT | BLU & WHT/BLK | DR1 & PR1, DR2 & DR1 & PR1 & PR2, DR3 & DR2 & PR2 & PR3, DR3 & PR3, DA & PA, REPEAT | SAME AS MODE 2 (SWEEP) |

## CONTROL WIRES FOR OPTIONAL HALOGENS

| CONTROL WIRE ACTIVATED | | HALOGEN LAMP |
|---|---|---|
| BROWN | PF1 | (TAKEDOWN) |
| RED/WHITE | DF1 | (TAKEDOWN) |
| GRAY | DA | (DRIVER ALLEY) |
| YELLOW | PA | (PASSENGER ALLEY) |

**NOTE: GREEN control wire activates high intensity to strobes.**
**Apply +12vdc to appropriate control wire to activate desired function.**
**Cut loop (22 AWG BLACK) on 930F-0030 (FRONT power supply) to disable FRONT strobes during traffic direction modes.**