

# 930N-5606-0059 FLASH PATTERN

## LIGHTBAR LAMP CONFIGURATION

	DF3	DF2	DF1	PF1	PF2	PF3	
DC							PC
DA							PA
	DR3	DR2L/DR2R	DR1L/DR1R	PR1L/PR1R	PR2L/PR2R	PR3	

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES & HALOGENS	FRONT / CORNER STROBES & HALOGENS
1	ORG & RED/WHT  (REAR ONLY)	<u>STROBES</u> DR3 ALTERNATES WITH PR3 <u>HALOGENS</u> DR2L ALTERNATES WITH PR2R	NONE
2	ORG, RED/WHT & BLU	SAME AS MODE 1	<u>STROBES</u> DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS
3	ORG, RED/WHT, BLU & WHT/BLK	SAME AS MODE 1	<u>STROBES</u> DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS DC ALTERNATES WITH PC

### CONTROL WIRES FOR STANDARD HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP
BRN/WHT	PF1 (TAKEDOWN)
BRN	DA & PA (SOLID ALLEY FLASHERS)

### OPTIONAL CONTROL WIRES

CONTROL WIRE ACTIVATED	HALOGEN LAMP
GRAY	DA (DRIVER ALLEY)
YELLOW	PA (PASSENGER ALLEY)
BRN	DA, PA, DF1L & PF1R (SPLIT ALLEY & FRONT FLASHER)
BRN/WHT	DF1 & PF1 (SPLIT or SOLID TAKEDOWN)

\*\* Split Alley - Front Flasher option only available when Alley Light Option is ordered

### CONTROL WIRE FOR PRE2-1C

CONTROL WIRE ACTIVATED	PREEMPTION EMITTER
BRN/WHT	DF1 or PF1

\*\* PRE2-1C option eliminates Takedown Option

**NOTE: GREEN control wire activates high intensity to strobes.**  
**Apply +12vdc to appropriate control wire to activate desired function.**

### CONTROL WIRES FOR CUSTOMER CONTROLLED HALOGEN ARROW

TOMAR M1072 CABLE	HALOGEN LAMP
YELLOW	PR2R
YELLOW/WHITE	DR1L
RED	DR1R
RED/WHITE	PR1L
BLACK	PR1R
BLACK/WHITE	PR2L

**Apply -12vdc to appropriate control wire to activate desired function.**