930N-6407-0016 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF3 DF2 DF1 FC PF1 PF2 PF3
DC PC
DA PA
DR3 DR2 DR1 RC PR1 PR2 PR3

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES	FRONT / CORNER STROBES
0	NONE	NONE	NONE
1	ORG	DR1 ALTERNATES WITH PR1	NONE
2	ORG & BLU	DR2, PR2 & DA SIMULTANEOUS AND ALTERNATE WITH DR1, PR1 & PA SIMULTANEOUS	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS
3	ORG & BLU & WHT/BLK	SAME AS MODE 2	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS DC ALTERNATES WITH PC DF1 ALTERNATES WITH PF1
4	BLU (RIGHT ARROW)	DR2, DR2 & DR1, DR1 & PR1, PR1 & PR2, PR2, DA & PA, REPEAT	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS
5	WHT/BLK (LEFT ARROW)	PR2, PR2 & PR1, PR1 & DR1, DR1 & DR2, DR2, DA & PA, REPEAT	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS DF1 ALTERNATES WITH PF1
6	BLU & WHT/BLK (CENTER OUT)	DR1 & PR1, DR2 & DR1 & PR1 & PR2, DR2 & PR2, DA & PA, REPEAT	DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF2 & PF2 SIMULTANEOUS DF1 ALTERNATES WITH PF1

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP	
RED/WHITE	RC	(REAR WORK)
BROWN	FC	(TAKEDOWN)
BROWN/WHITE	DR3 & PR3	(TAIL LIGHTS)
GRAY	DR3	(LEFT TURN)
YELLOW	PR3	(RIGHT TURN)

ADDITIONAL 6/C CONTROL CABLE FOR OPTIONAL HALOGENS

CONTROL WIRE	HALOGEN LAMP	
RED	DA	(DRIVER ALLEY)
YEL	PA	(PASSENGER ALLEY)
RED/WHT	DF2/PF2 or DF1/PF1	(SPLIT TAKEDOWN or SPLIT FLASHER)

NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.