

930NH-7208 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF4	DF3	DF2	DF1	PF1	PF2	PF3	PF4
DC							PC
DA							PA
DR4	DR3	DR2	DR1	PR1	PR2	PR3	PR4

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES & HALOGENS	FRONT / CORNER STROBES & HALOGENS
1	ORG	<p style="text-align: center;"><u>STROBES</u></p> <p>DR2 ALTERNATES WITH PR2 (4 PULSES PER BURST)</p> <p style="text-align: center;"><u>HALOGENS</u></p> <p>DR1 ALTERNATES WITH PR1</p>	<p style="text-align: center;"><u>STROBES</u></p> <p>DF2 ALTERNATES WITH PF2 (4 PULSES PER BURST)</p>
2	ORG & BLU	<p style="text-align: center;"><u>STROBES</u></p> <p>DR4, PR4 & DA SIMULTANEOUS AND ALTERNATE WITH DR2, PR2 & PA SIMULTANEOUS (6 PULSES PER BURST)</p> <p style="text-align: center;"><u>HALOGENS</u></p> <p>DR3 ALTERNATES WITH PR3 DR1 ALTERNATES WITH PR1</p>	<p style="text-align: center;"><u>STROBES</u></p> <p>DF4, PF4 & DC SIMULTANEOUS AND ALTERNATE WITH DF2, PF2 & PC SIMULTANEOUS (6 PULSES PER BURST)</p> <p style="text-align: center;"><u>HALOGENS</u></p> <p>DF3 ALTERNATES WITH PF3 DF1 ALTERNATES WITH PF1</p>
3	ORG & BLU & WHT/BLK	SAME AS MODE 2	SAME AS MODE 2

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED	HALOGEN LAMP
YELLOW	PA (PASSENGER ALLEY)
GRAY	DA (DRIVER ALLEY)
RED/WHITE	DR1 & PR1 (SPLIT REAR WORK LIGHTS)
BROWN	DF1 & PF1 (SPLIT FRONT TAKEDOWNS)

**NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.**